

marantz

Value Electronics
914-723-3344



SR6015

www.ValueElectronics.com

Marantz SR6015 9.2ch 8K AV amplifier with HEOS Built-in and Voice Control

Drive exquisitely detailed home cinema with this powerful AV amplifier. Delight in the most musical sound for any source - from movies, to vinyl, to digital streaming. It's the perfect sonic accoutrement for any occasion. Totally immerse yourself in movies and TV with elevated, high-resolution surround sound through Dolby Atmos, DTS:X and IMAX Enhanced. Stream music from leading services, and listen to music in your whole home with HEOS Built-in.

- Performance, power and connectivity to suit your audio preferences: 9.2 channel discrete power amplifier, 185W per channel, with 11.2 channel processing capability to further expand the system.
- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices or with 8K upscaling from Full HD or 4K sources.
- Support for the most advanced three-dimensional audio formats: Dolby Atmos, Dolby Atmos Height Virtualization Technology, DTS:X, DTS Virtual:X and IMAX Enhanced processing are all supported to allow you to listen to immersive, multi-dimensional audio.
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV with eARC HDMI support to allow uncompressed and object-based audio formats like Dolby Atmos and DTS:X directly from a smart TV app to your AV amplifier.
- The greatest technology for home cinema: Support for the latest HDR formats including HDR10, HDR10+, HLG, Dolby Vision, 4:4:4 colour resolution and BT.2020, as well as Dynamic HDR provides exceptional picture quality for brightness, clarity and contrast.
- Advanced gaming specifications: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), experience gaming thrills with amazing imaging and reduced lag.
- High-resolution streaming for audiophile approved sound: Play back ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz as well as DSD 2.8MHz and 5.6MHz tracks, and enjoy your music exactly as the artist intended.
- Exclusive components elevate the Marantz sonic signature: Marantz proprietary HDAM circuit boards, Current Feedback circuitry, AKM AK4458 32-bit D/A converters, and Hybrid PLL Clock Jitter Reducer produce more detailed, dynamic sound.
- Almost unlimited music sources: Stream from music services like Spotify Free and Premium, Amazon Music HD, Tidal and more, or stream directly from smart devices via AirPlay 2 or Bluetooth
- Features HEOS Built-in and the free HEOS App: Your key to digital music streaming, multi-room audio and voice control throughout your entire home.

Modern Musical Luxury



SR6015

Technical Specs



Multichannel surround		
DTS HD Master / DTS:X / DTS:X Pro	• / • / -	
DTS Neo:X / DTS Neural:X	- / •	
DTS Virtual:X	•	
IMAX Enhanced	•	
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization	• / • / •	
Dolby ProLogic IIz / Dolby Surround	- / •	
Auro 3D	-	
Multichannel Stereo	•	
Max Number of Processing (Preamp) Channels	11.2	
Sound Enhancements		
Discrete Power Amplifier	9	
Copper Plated Chassis	-	
Power Transformer: Toroidal / EI	EI	
Current Feedback Topology	•	
Hyper Dynamic Amplifier Modules (HDAM)	•	
Pure Direct	•	
Gold Plated RCA Terminals	•	
Clock Jitter Reducer	•	
Audyssey	MultEQ XT32	
Audyssey Dynamic EQ / Dynamic Volume	• / •	
Audyssey LFC	•	
Compressed Audio Enhancer: MDAX2	•	
Network		
HEOS Multi-room and Streaming	•	
Bluetooth Re-transmit for Bluetooth headphones	•	
Amazon Alexa / Google Voice Assistant / Apple HomePod	• / • / •	
Lossy Formats: MP3 / WMA / AAC	• / • / •	
Lossless Formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •	
DSD Audio Streaming	• (2.8/5.6MHz)	
FLAC HD 192/24	•	
Gapless Playback	• (FLAC, WAV, ALAC, DSD)	
AirPlay Audio Streaming	• (AirPlay2)	
Internet Radio	• (Tuneln)	
Spotify	• (connect)	
Amazon Music HD / Deezer / TIDAL / Napster / others	• / • / • / • / varies per region	
Compatible with Remote APP for Smart Phones	Android / iOS	
Compatible with Remote APP for Tablets	Android / iOS / Amazon Kindle	
Ethernet Port	•	
Wi-Fi	•	
Bluetooth	•	
HDMI		
HDMI Inputs: Back / Front	7 / 0	
HDCP2.3 support	•	
HDMI Outputs: Main / Zone	2 / 1	
Video Conversion Analogue -> HDMI	•	
HDMI to HDMI scaling	up to 8K 60/50Hz	
8K/60Hz / 4K/120Hz / CEC / eARC	• / • / • / •	
Dolby Vision / HDR10+ / Dynamic HDR / HLG	• / • / • / •	
ALLM (Auto Low Latency Mode) Pass-through for gaming	•	
Variable Refresh Rate / Quick Frame Transport / Quick Media Switching	• / • / •	
HDMI pass-through in Standby Mode	•	
DSD Audio Capability	•	
Auto LipSync	•	
Multiroom / CI		
HEOS Multi-Room Integrated	•	
TV Sound Grouping	•	
Multi-Room zones	2	
Zone Audio Source: HDMI / Opt. Coax / Network, USB / Analogue	• (2ch) / • (2ch) / • / •	
Zone Audio Output: Speaker / Preout	• / •	
Zone HDMI Output from HDMI Source	•	
IP Control / RS232 Control / Web Control / App Control	• / • / • / •	
IR Flasher In	•	
Marantz Remote Bus	•	
DC Trigger Output	1	
HDMI Diagnostics	•	

Others		
Auto Speaker Setup by Microphone		Audyssey MultEQ XT32
FL Display		Port Hole
Graphic User Interface - GUI		Advanced
ISF Certification		•
GUI Languages		9
Setup Assistant		•
Smart Select		•
Firmware Update by Network / USB		• / •
Variable Cross Over		•
Optimized Bass Redirection		•
Bass Sync		-
ECO Mode		•
Auto Power Off		•
Sleep Timer		•
Video Inputs/Outputs		
Composite In / Out		3+1 / 1
Component In / Out		2 / 1
HDMI In / Out		7 / 3
Multi-Room Video Out: Video / HDMI		- / •
Audio Inputs/Outputs		
Analogue In / Out		6+1 / -
Phono (MM) In		•
Digital In: Optical / Coaxial		2 / 2
Multi-Room Out: Analogue / Digital		1 / -
Multichannel Pre Out		• ((11.2))
Subwoofer Out		2
7.1 Multichannel Input		•
Other		
Speaker Terminal: Gold Plated Screw / Regular Screw		• / -
Number of Speaker Terminals		11
Speaker A / B		assignable
Bi-Amp Drive		assignable
Multi-Room Speaker Terminal		assignable
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB		• / • / - / • / •
USB Audio		•
FM/AM Tuner		-
General Power		
Number of Poweramps		9
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)		110 W
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)		150 W
Power Output (6 ohm, 1 kHz, 1% 1ch Drive)		185 W
70% Guarantee		•
General		
Metal Front Panel		•
System Remote Control		RC042SR
Pre-Programmed / Learnable / LCD Display		- / - / -
Power Consumption in W		680
Power Consumption No-Sound (ECO on / off) in W		60 W / 100 W
Standby Consumption in W		0.2
CEC Standby Consumption in W		0.5
Network Standby Consumption in W		3.7
Maximum Dimensions in mm		
Antenna:Horizontal:(W x D x H)		440 x 398 x 161
Antenna:Vertical:(W x D x H)		440 x 398 x 229
w/o Antenna:(W x D x H)		440 x 388 x 161
Weight in kg		
Carton Maximum Dimensions (W x D x H) in mm		537 x 483 x 257
Carton Weight (incl. product) in kg		15.4
SAP Code / EAN Black		SR6015/N1B 4951035073056
SAP Code / EAN Silver-Gold		SR6015/N1SG 4951035073063

Value Electronics
914-723-3344

www.ValueElectronics.com

Sound United
A Division of D&M Europe B.V.
P.O. Box 8744
5605 LS Eindhoven
The Netherlands



Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

www.marantz.com